ACCESSORY AIR DRIVE 200 FT-LBS

- Powered input to a torque multiplier can reduce operator fatigue, increase productivity.
- ▶ Designed to drive Proto® Torque Multipliers (except J6202A).
- Maximum torque output: 200 ft-lbs (271 Nm).
- Maximum running air pressure: 60 PSI.
- Output free speed: 70 RPM.
- Output rotation: clockwise and counterclockwise.

Product #	Drive Size (in)	Output Drive (in)	Diameter Maximum (in)	Overall Length (in)	Weight (lbs)
J6201	1/2	1/2 Sq. Male	3-1/8	16-1/4	11.00



AIR DRIVE CONVERTER 200 FT-LBS

- > Powered input to a torque multiplier can reduce operator fatigue, increase productivity.
- Designed to drive Proto® Torque Multipliers (except J6202A) when used with an air or electric drive tool.
- Not designed for use with Impact Tools.
- Maximum torque output: 200 ft-lbs (271 Nm).
- Maximum torque input: 38 ft-lbs (52 Nm).



Product #	Drive Size (in)	Input Drive (in)	Output Drive (in)	Torque Ratio	Diameter (in)	Overall Length (in)	Weight (lbs)	
J6203	1/2	1/2	1/2 Sq. Male	1:5.2	3-1/8	4	5.50	
•								=




3/8" DRIVE 9 PIECE TORQUE ADAPTER SET - 12 POINT

Product #: J5100

Contents	Description
J5112	Torque Adapter 3/8"
J5114	Torque Adapter 7/16"
J5116	Torque Adapter 1/2"
J5118	Torque Adapter 9/16"
J5120	Torque Adapter 5/8"
J5122	Torque Adapter 11/16"
J5124	Torque Adapter 3/4"
J5126	Torque Adapter 13/16"
J5128	Torque Adapter 7/8"

Weight (lbs): 1.32


AS954E S3.8.1



- Adapters measure 2" from the center of the square drive to the center of the adapter opening.
- Special heat-treated alloy steel helps to increase strength and durability.
- Box end wall thickness is specially engineered to provide strength while still allowing ample room for access to reach difficult fasteners.
- 12 point box end allows for fine indexing, helping to improve speed and access. Fits 4, 6 and 12 point fasteners.









Product #	Size (in)	Drive Size (in)	Head Width (in) (B)	Head Depth (in) (C)	Overall Length (in) (L)	Weight (lbs)
J5112	3/8	3/8	9/16	17/64	2-11/16	0.08
J5114	7/16	3/8	21/32	19/64	2-47/64	0.10
J5116	1/2	3/8	47/64	21/64	2-25/32	0.10
J5118	9/16	3/8	13/16	23/64	2-13/16	0.12
J5120	5/8	3/8	29/32	25/64	2-55/64	0.12
J5122	11/16	3/8	1	27/64	2-29/32	0.12
J5124	3/4	3/8	1-5/64	29/64	2-61/64	0.12
J5126	13/16	3/8	1-11/64	31/64	2-63/64	0.14
J5128	7/8	3/8	1-17/64	33/64	3-1/32	0.16

AS954E S3.8.1

