

XTi

There's no debate – when you choose Crown's XTi 2 Series, you're choosing one of the most powerful and innovative amplifiers on the market today. That's because the all-new XTi 2 Series amps continue to set the standard for unmatched performance and value, delivering the goods night after night without breaking a sweat.

With such innovations as a universal tracking switch-mode power supply and a fully integrated suite of speaker processing tools, these amps are at the top of their class when it comes to thermal efficiency and system flexibility.

You also have greatly improved control capabilities. The addition of Peakx Plus™ Limiters gives you full command over threshold, attack and release, and we enhanced the Subharmonic Synth so you can easily manage frequency, gain and filter type, allowing for application-specific tuning.

Plus, you'll now be able to tailor fan speed for specific applications and have software visibility of the Power Supply Temperature and AC Line Voltage. Combine all of that with integrated cast-aluminum rack handles for maximum durability and portability and you have the power to move you – and the world.

NEXT GENERATION FEATURES:

- Peakx Plus™ Limiters provide the ultimate in system performance and protection by allowing full control over threshold, attack, and release
- Enhanced Subharmonic Synth section provides user control over frequency, gain and filter type for system-specific tuning
- 3 User-defined fan mode controls – normal, early and full-speed – for matching fan performance to a specific application
- New system monitoring provides software visibility of AC line voltage and power supply temperature
- Increased number of presets to a total of 30; 29 of which are user definable
- Integrated cast-aluminum handles for easy handling and enhanced durability
- Locking power cord clip provides a secure connection between the amplifier and power cord
- Updated HiQnet Band Manager™ and System Architect™ control software

XTi 1002

2Ω Stereo (per channel)	700W
4Ω Stereo (per channel)	500W
8Ω Stereo (per channel)	275W
8Ω Bridge - Mono	1,000W
4Ω Bridge - Mono	1,400W

XTi 2002

2Ω Stereo (per channel)	1,000W
4Ω Stereo (per channel)	800W
8Ω Stereo (per channel)	475W
8Ω Bridge - Mono	1,600W
4Ω Bridge - Mono	2,000W

XTi 4002

2Ω Stereo (per channel)	1,600W
4Ω Stereo (per channel)	1,200W
8Ω Stereo (per channel)	650W
8Ω Bridge - Mono	2,400W
4Ω Bridge - Mono	3,200W

XTi 6002

2Ω Stereo (per channel)	3,000W
4Ω Stereo (per channel)	2,100W
8Ω Stereo (per channel)	1,200W
8Ω Bridge - Mono	4,200W
4Ω Bridge - Mono	6,000W



PERFORMANCE

Sensitivity (for full rated power at 4 ohms):
1.4 Vrms

Frequency Response
(at 1 watt, 20 Hz to 20 kHz): +0 dB, -1 dB

Signal-to-Noise Ratio (below rated 1kHz power at 8 ohms):
XTi 1002/2002/4002: 100 dB (A weighted),
XTi 6002: 103 dB (A weighted)

Total Harmonic Distortion (THD): < 0.5%

Damping Factor 20 Hz to 1 kHz: > 500

Crosstalk (below rated power):
20 Hz - 1 kHz: > 70 dB

Input Impedance (nominal):
20k ohms balanced, 10k ohms unbalanced

Maximum Input Signal: +22 dBu typical

AC Line Voltage and Frequency Configurations:
100 VAC, 120 VAC, 220-240 VAC 50/60 Hz

AC Line Current (120 VAC amplifier playing 1/8 power pink noise into 4 ohms per ch):
XTi 1002: 6.8A; no more than 38W at idle,
XTi 2002: 8.3A; no more than 38W at idle,
XTi 4002: 10.5A; no more than 38W at idle,
XTi 6002: 15.3A; no more than 180W at idle

Operating Temperature:
0°C to 40°C at 95% relative humidity
(non-condensing)

INDICATORS

Signal Indicator: Green LED, one per channel, illuminates when a very low-level signal is present at input (may be used for troubleshooting cable runs).

-10 Indicator: Green LED flashes when output signal exceeds -10 dB below clip.

-20 Indicator: Green LED flashes when output signal level exceeds -20 dB below clip.

Ready Indicator: Green LED, one per channel, illuminates when the amplifier is ready to produce audio.

Clip Indicator: Red LED, one per channel, turns on at the threshold of audible distortion.

Temp Indicator: Red LED, one per channel, illuminates under excessive temperature conditions.

Power Indicator: Blue LED illuminates when the amplifier has been turned on and has power.

CONTROLS

Level: Two front-panel rotary level controls, one for each channel.

Power Switch: On/Off switch applies AC power to the amplifier.

Sel/Prev/Next Buttons: Three buttons near the LCD screen that are used to access menu items and front panel lockout.

LCD Screen: Backlit liquid crystal display that shows preset and processing status.

INTEGRATED PROCESSING

Input EQ: 6 parametric filters per channel with adjustable Q, ±15 dB boost/cut. Also adjustable high and low shelving filters. This 8-filter EQ section can be bypassed.

Crossover Filters: Highpass and Lowpass per channel. Butterworth 6/12/18/24 dB per octave. Linkwitz-Riley 24/48 dB per Octave. Also includes ± 15 dB bandpass gain and polarity control.

Output EQ: 8 parametric filters per channel with adjustable Q, ±15 dB boost/cut. This 8-filter EQ section can be bypassed.

Delay: For signal alignment of driver; 50 ms of total delay.

SubHarmonic Synth: Takes the low-frequency content of the input signal and "synthesizes" a new signal that is the same as the input signal but one octave lower. The new synthesized signal is then mixed with the original signal to create the effect. New: Users now have control over frequency, gain, and filter type.

Peak™ Plus Limiter: User defeatable limiter that allows users to control Threshold, Attack, and Release times.

Presets: 30 total presets, 29 of which are user-definable.

INPUT/OUTPUT CONNECTORS

Input Connectors: XLR, one per channel)

Link/Out Connector: Loop-thru signal from input connector for linking another amplifier, one per channel.

Output Connectors: Two Neutrik® Speakon® NL4MP output connectors. Channel-1 Speakon® is wired with Ch. 1 and Ch. 2 outputs for use with optional single 4-conductor cable. Two binding post outputs (in parallel with Speakon® connectors).

HiQnet™ USB Connector: Type B, connects to HiQnet™ network.

CONSTRUCTION

Chassis: Steel

Front Panel: Cast-aluminum

Cooling: Proportional speed fan with front-to-rear airflow.

Dimensions:

XTi 1002/2002/4002: 19" (W) x 3.5" (H) x 12.25" (D),

XTi 6002: 19" (W) x 3.5" (H) x 16.2" (D)

Net Weight:

XTi 1002/2002/4002: 18.5 lbs (8.4kg),
XTi 6002: 24.0 lbs (10.9kg)

Shipping Weight:

XTi 1002/2002/4002: 21.5 lbs (9.8kg),
XTi 6002: 30.0 lbs (13.6kg)



Crown International
1718 W. Mishawaka Rd.
Elkhart, IN 46517-9439
TEL: 574-294-8200
FAX: 574-294-8FAX
CrownAudio.com



Specifications subject to change without prior notice. Latest information available at CrownAudio.com.

Crown and Crown Audio are registered trademarks of Crown International. Other trademarks are the property of their respective owners. Printed in U.S.A.

© 2010 Crown Audio, Inc.