

Item: 88213-SU, 88214-SU, 88269-SU, 88271-SU, 88273-SU, 88275-SU



Ballast Description					Reduced Lamp Load*		Rated Lamp Load	
No.	Brand	Model	Start Method	No. of Lamps	120V	277V	120V	277V
1	AC Electronics	CSD-UV42PS	PS	2	✓	✓	✓	✓
2	AC Electronics	CSS-UV42PS	PS	2	✓	✓	✓	✓
3	Espen	VE126120MR	PS	1	N/A	N/A	✓	N/A
4	Fulham	RHA-UNV-226-C	PS	2	✓	✓	✓	✓
5	Fulham	RHA-UNV-242-C	PS	2	N/A	N/A	✓	✓
6	Fulham	WH2-120-C	IS	1	N/A	N/A	✓	N/A
7	Fulham	WH3-120-L	IS	2	N/A	N/A	✓	N/A
8	Fulham	NPY-120-126CFL	RS	1	N/A	N/A	✓	N/A
9	Fulham	NPY-120-226CFL	RS	2	N/A	N/A	✓	N/A
10	Fulham	WH3-120-C	IS	1	N/A	N/A	✓	N/A
11	Hatch	HC218PS/UV/D	PS	1	N/A	N/A	✗	✗
12	Hatch	HC226PS/UV/D	PS	2	✗	✗	✗	✓
13	Hatch	HC242PS/UV/D	PS	2	N/A	N/A	✗	✓
14	Howard Industries	EP2/42CF/MV/2	PS	2	✗	✗	✗	✓
15	Keystone	KTEB-126-1-TP	PS	1	N/A	N/A	✓	N/A
16	Keystone	KTEB-126-1-TP-SC-RJS /HB	PS	1	N/A	N/A	✓	N/A
17	Keystone	KTEB-218-UV-PS-DW	PS	1	N/A	N/A	✗	✗
18	Keystone	KTEB-218-UV-RS-DW	RS	1	N/A	N/A	✓	✓
19	Keystone	KTEB-226-1-TP	PS	2	N/A	N/A	✓	N/A
20	Keystone	KTEB-226-UV-PS-DW	PS	2	✗	✗	✗	✓
21	Keystone	KTEB-226-UV-RS-DW	RS	2	✓	✓	✓	✓
22	Keystone	KTEB-242-UV-RS-DW	RS	2	✗	✗	✓	✓
23	Motorola	M2-CF-26-B-S-277	RS	2	N/A	N/A	N/A	✓
24	Osram Sylvania	QTP 2×26/32/42CF/UNV DM	PS	2	N/A	N/A	✗	✓
25	Osram Sylvania	QTP 2×26/32/42CFUNV DM PE	PS	2	N/A	N/A	✓	✓

Ballast Description					Reduced Lamp Load*		Rated Lamp Load	
No.	Brand	Model	Start Method	No. of Lamps	120V	277V	120V	277V
26	Osram Sylvania	QTP 2x26CF/UNV DM	PS	2	✓	✓	✓	✓
27	Philips Advance	ICF-2S26-H1-LD	PS	2	✓	✓	✓	✓
28	Philips Advance	ICF-2S26-M1-BS	PS	2	✓	✓	✓	✓
29	Philips Advance	ICF-2S42-M2-LD	PS	2	N/A	N/A	✓	✓
30	Philips Advance	RCF-2S26-M1-LS-QS	RS	2	✓	N/A	✓	N/A
31	ProLume	EP2CF18PS/MV/DC/K	PS	1	N/A	N/A	✓	✓
32	ProLume	EP2CF26PS/MV/DC/K	PS	2	✗	✗	✗	✗
33	Robertson	RSO142TR120	RS	1	N/A	N/A	✓	N/A
34	Sunpark	U-226PS-W	PS	2	✓	✓	✓	✓
35	Tospo	TP120-2/26 RS UPL	RS	2	N/A	N/A	✗	N/A
36	Universal Lighting Technologies	eC2642UNVBE	PS	2	✓	✓	✓	✓
37	Universal Lighting Technologies	eC2642UNVME	PS	2	✓	✓	✓	✓