

Tripp Lite 1111 W. 35th Street Chicago, IL 60609 USA Telephone: 773.869.1234 www.tripplite.com

# SmartPro 120V 750VA 600W Line-Interactive Sine Wave UPS, 1U Rackmount, Network Management Card Options, USB, DB9 Serial

# MODEL NUMBER: SMART750RM1U





## Description

Tripp Lite SMART750RM1U 750VA / .75kVA / 600 watt line interactive, sine wave UPS system offers complete power protection for critical network applications in a highly efficient 1U total rack/tower configuration. Simultaneous-use network management interfaces include USB, RS-232 and slot for optional Network Management Card options. Line interactive voltage regulation, network-grade surge suppression and long-lasting sine wave AC output during blackouts make this UPS ideal for advanced networking applications in datacenters, computer rooms and network closets.

#### Features

- Tripp Lite SMART750RM1U .75kVA / 750VA / 600 watt line interactive UPS
- 1U rack/tower compatible form factor
- Included mounting brackets support 2 and 4 post rackmount installation; Optional 4POSTRAILKIT1U is available for additional support
- NEMA 5-15P input; 6 5-15R output receptacles
- Installed depth of only 16.75 in. / 42.5cm
- Sine wave output in both AC and battery backup modes
- Line Interactive UPS provides Automatic Voltage Regulation / AVR to maintain 120V nominal output during brownouts to 83V and overvoltages to 147V without using battery power
- Full load efficiency rating of 98% saves energy and ensures cool operating temperatures
- Integrated 2 bank switched PDU enables remote outlet management for load shedding or remote reboot of individual devices
- USB & Serial ports enable data-saving unattended shutdown when used with Tripp Lite's PowerAlert software, available via FREE download from <u>www.tripplite.com/poweralert</u>

### Highlights

- .75kVA / 750VA / 600W line interactive 1U rackmount UPS, Sine wave output
- 120V output, Corrects brownouts and overvoltages from 83V to 147V
- 0.8 Power Factor, Front panel status LEDs
- Mounting brackets support 2 and 4 post installation
- 98% line-mode efficiency, 2 switched load banks
- USB, RS232, EPO and slot for Network Management Card options
- 120V NEMA 5-15P input, 6 NEMA 5-15R outlets
- To use the Auto Probe feature, this product requires a WEBCARDLX network interface (sold separately) running LX firmware update 15.5.2 or later

#### **Package Includes**

- SMART750RM1U UPS System
- Mounting hardware
- USB, DB9 and EPO Cabling
- Instruction manual



- HID-compliant USB interface enables integration with built-in power management and auto shutdown features of Windows and Mac OS X
- Compatible with Tripp Lite UPS management card options TLNETCARD, WEBCARDLX and SNMPWEBCARD
- 3 stage metered LEDs offer current monitoring and battery charge level
- Mains power and voltage regulation LEDs offer at-a-glance power status information
- Front panel switches support self-test and alarm cancel functions
- Field replaceable, hot-swappable internal UPS batteries

# **Specifications**

OVERVIEW		
UPC Code	037332118813	
UPS Type	Line-Interactive	
INPUT		
Rated input current (Maximum Load)	7A	
Nominal Input Voltage(s) Supported	120V AC	
UPS Input Connection Type	5-15P	
Input Circuit Breakers	15A	
Recommended Electrical Service	15A 120V	
Input Phase	Single-Phase	
Input Cord Length (ft.)	10	
Input Cord Length (m)	3.05	
OUTPUT		
Output Volt Amp Capacity (VA)	750	
Output Watt Capacity (Watts)	600	
Power Factor	0.8	
Nominal Voltage Details	120v nominal output in battery mode	
Frequency Compatibility	60 Hz	
Output Voltage Regulation (Line Mode)	-21%, +8%	
Output Voltage Regulation (Battery Mode)	+/- 5%	
Load Management Receptacles	Two switchable single-outlet 5-15R load banks	
Output AC Waveform (AC Mode)	Sine wave	



Output AC Waveform (Battery Mode)	Pure Sine wave
Nominal Output Voltage(s) Supported	110V; 115V; 120V
Output Receptacles	(6) 5-15R
Individually Controllable Load Banks	Yes
BATTERY	
Full Load Runtime (min.)	4.9 min. (600w)
Half Load Runtime (min.)	13.2 min. (300w)
DC System Voltage (VDC)	24
Battery Recharge Rate (Included Batteries)	Less than 4 hours from 10% to 90% (typical, full load discharge)
Internal UPS Replacement Battery Cartridge	<a class="productLink" href="//www.tripplite.com/1U-UPS-Replacement-24VDC-Battery-Cartridge-1-Set-4-&lt;br&gt;for-Select-Tripp-Lite-SmartPro-UPS~RBC64-1U">RBC64-1U-/a&gt; </a>
Battery Access	Front panel battery access door
Battery Replacement Description	Hot-swappable, user replaceable batteries
Expandable Runtime	No
VOLTAGE REGULATION	
VOLTAGE REGULATION	Automatic voltage regulation (AVR) maintains line power operation with an input voltage range of 83 to 147
VOLTAGE REGULATION Voltage Regulation Description	
VOLTAGE REGULATION Voltage Regulation Description Overvoltage Correction	Automatic voltage regulation (AVR) maintains line power operation with an input voltage range of 83 to 147
VOLTAGE REGULATION Voltage Regulation Description Overvoltage Correction Undervoltage Correction	Automatic voltage regulation (AVR) maintains line power operation with an input voltage range of 83 to 147         Input voltages between 128 and 147 are reduced by 12%         Input voltages between 83 and 107 are boosted by 14%
VOLTAGE REGULATION Voltage Regulation Description Overvoltage Correction Undervoltage Correction USER INTERFACE, ALERTS & CON	Automatic voltage regulation (AVR) maintains line power operation with an input voltage range of 83 to 147         Input voltages between 128 and 147 are reduced by 12%         Input voltages between 83 and 107 are boosted by 14%
VOLTAGE REGULATION Voltage Regulation Description Overvoltage Correction Undervoltage Correction USER INTERFACE, ALERTS & CON Switches	Automatic voltage regulation (AVR) maintains line power operation with an input voltage range of 83 to 147         Input voltages between 128 and 147 are reduced by 12%         Input voltages between 83 and 107 are boosted by 14%
VOLTAGE REGULATION Voltage Regulation Description Overvoltage Correction Undervoltage Correction USER INTERFACE, ALERTS & CON Switches Alarm Cancel Operation	Automatic voltage regulation (AVR) maintains line power operation with an input voltage range of 83 to 147         Input voltages between 128 and 147 are reduced by 12%         Input voltages between 83 and 107 are boosted by 14%         TROLS         2 Switches control off/on power status and alarm-cancel/self-test operation         Power-fail alarm can be silenced using alarm-cancel switch; once silenced, alarm will re-sound to indicate low-
•	Automatic voltage regulation (AVR) maintains line power operation with an input voltage range of 83 to 147         Input voltages between 128 and 147 are reduced by 12%         Input voltages between 83 and 107 are boosted by 14%         TROLS         2 Switches control off/on power status and alarm-cancel/self-test operation         Power-fail alarm can be silenced using alarm-cancel switch; once silenced, alarm will re-sound to indicate low-battery status
VOLTAGE REGULATION Voltage Regulation Description Overvoltage Correction Undervoltage Correction USER INTERFACE, ALERTS & CON Switches Alarm Cancel Operation Audible Alarm LED Indicators	Automatic voltage regulation (AVR) maintains line power operation with an input voltage range of 83 to 147         Input voltages between 128 and 147 are reduced by 12%         Input voltages between 83 and 107 are boosted by 14%         TROLS         2 Switches control off/on power status and alarm-cancel/self-test operation         Power-fail alarm can be silenced using alarm-cancel switch; once silenced, alarm will re-sound to indicate low-battery status         Audible alarm indicates power-failure, overload and low-battery conditions
VOLTAGE REGULATION Voltage Regulation Description Overvoltage Correction Undervoltage Correction USER INTERFACE, ALERTS & CON Switches Alarm Cancel Operation Audible Alarm LED Indicators SURGE / NOISE SUPPRESSION	Automatic voltage regulation (AVR) maintains line power operation with an input voltage range of 83 to 147         Input voltages between 128 and 147 are reduced by 12%         Input voltages between 83 and 107 are boosted by 14%         TROLS         2 Switches control off/on power status and alarm-cancel/self-test operation         Power-fail alarm can be silenced using alarm-cancel switch; once silenced, alarm will re-sound to indicate low-battery status         Audible alarm indicates power-failure, overload and low-battery conditions
VOLTAGE REGULATION Voltage Regulation Description Overvoltage Correction Undervoltage Correction USER INTERFACE, ALERTS & CON Switches Alarm Cancel Operation Audible Alarm	Automatic voltage regulation (AVR) maintains line power operation with an input voltage range of 83 to 147         Input voltages between 128 and 147 are reduced by 12%         Input voltages between 83 and 107 are boosted by 14%         TROLS         2 Switches control off/on power status and alarm-cancel/self-test operation         Power-fail alarm can be silenced using alarm-cancel switch; once silenced, alarm will re-sound to indicate low-battery status         Audible alarm indicates power-failure, overload and low-battery conditions         5 LEDs indicate line power, battery power, overload, voltage regulation and battery low/replace status

#### PHYSICAL

Cooling Method	Fan
Included Mounting Accessory Description	Included mounting brackets provide front-rail installation in 2 or 4 post racks; For additional stability in 4 post racks, consider optional 4 post mounting accessories 4POSTRAILKIT1U & 4POSTRAILKITWM



COMMUNICATIONS	
Audible Noise	45 dBA maximum, front side 1m
AC Mode Efficiency Rating (100% Load)	98%
Battery Mode BTU / Hr. (Full Load)	545
AC Mode BTU / Hr. (Full Load)	38
Relative Humidity	0 to 95%, non-condensing
Storage Temperature Range	+5 to +122 degrees Fahrenheit / -15 to +50 degrees Celsius
Operating Temperature Range	+32 to +104 degrees Fahrenheit / 0 to +40 degrees Celsius
ENVIRONMENTAL	
UPS Power Module Weight (lbs.)	30
UPS Power Module Weight (kg)	13.61
UPS Power Module Dimensions (hwd, in.)	1.75 x 17.5 x 16.75
UPS Power Module Dimensions (hwd, cm)	4.44 x 44.45 x 42.54
UPS Housing Material	Steel
Shipping Weight (lbs.)	34.10
Shipping Weight (kg)	15.47
Shipping Dimensions (hwd / in.)	5.20 x 23.10 x 20.70
Shipping Dimensions (hwd / cm)	13.21 x 58.67 x 52.58
Rack Height	10
Primary UPS Width (mm)	445
Primary UPS Height (mm)	44
Primary UPS Depth (mm)	425
Primary Form Factor	Kit~4POSTRAİLKIT1U">4POSTRAILKIT1U  enables installation in 4-post full-depth racks from 20.5 to 36 inches (521 to 914mm) Rackmount
Optional Mounting Accessory Notes	Optional <a class="productLink" href="//www.tripplite.com/4-Post-1U-Universal-Adjustable-Rack-Mount-Shelf-&lt;br&gt;Kit-for-Wall-Mount-Racks-4POSTRAILKITWM">4POSTRAILKITWM</a> enables installation in 4-port short- depth racks from 14.5 to 23.5 inches (368 to 597mm); Optional <a <br="" class="productLink">href="//www.tripplite.com/4-Post-1U-Universal-Adjustable-Rack-Mount-Shelf-</a>
Minimum Required Rack Depth (inches)	19.75
Minimum Required Rack Depth (cm)	50.16
Installation Form Factors Supported with Optional Accessories	4 post rackmount full-depth ( <a class="productLink" href="//www.tripplite.com/4-Post-1U-Universal-&lt;br&gt;Adjustable-Rack-Mount-Shelf-Kit~4POSTRAILKIT1U">4POSTRAILKIT1U</a> ); 4 post rackmount short- depth ( <a class="productLink" href="//www.tripplite.com/4-Post-1U-Universal-Adjustable-Rack-Mount-Shelf-&lt;br&gt;Kit-for-Wall-Mount-Racks~4POSTRAILKITWM">4POSTRAILKITWM</a> )
Installation Form Factors Supported with Included Accessories	2 post 19 inch rackmount; 2 post front mount; 4 post 19 inch rackmount; Tower



Network Management Cards	<a class="productLink" href="//www.tripplite.com/SNMP-Web-Management-Accessory-Card-SmartPro-&lt;br&gt;SmartOnline-UPS-Systems~SNMPWEBCARD">SNMPWEBCARD</a> ; <a <br="" class="productLink">href="//www.tripplite.com/Web-Management-Accessory-Card-SmartPro-SmartOnline-UPS- Systems~TLNETCARD"&gt;TLNETCARD</a> ; <a class="productLink" href="//www.tripplite.com/Web-&lt;br&gt;Management-Accessory-Card-WEBCARDLX">WEBCARDLX</a>
Network Monitoring Port Description	Supports detailed monitoring of UPS and site power conditions
PowerAlert Software	For local monitoring via the UPS's built-in communication ports, download PowerAlert Local software at http://www.tripplite.com/poweralert
Communications Cable	USB and DB9 cabling included
WatchDog Compatibility	Supports Watchdog application, OS and hard-reboot restart options for remote applications
Communications Interface	DB9 Serial; EPO (emergency power off); Slot for SNMP/Web interface; USB
LINE / BATTERY TRANSFER	
Transfer Time	5 milliseconds AC to DC; 1 millisecond DC to AC
Low Voltage Transfer to Battery Power (Setpoint)	83
High Voltage Transfer to Battery Power (Setpoint)	147
SPECIAL FEATURES	
Grounding Lug	Back panel grounding lug
Cold Start (Startup in Battery Mode During a Power Failure)	Cold-start operation supported
High Availability UPS Features	Hot swappable batteries; Auto Probe Monitoring and Reboot (requires WEBCARDLX)
STANDARDS & COMPLIANCE	
UPS Certifications	Tested to UL1778 (USA); Tested to CSA (Canada); Tested to NOM (Mexico); Meets FCC Part 15 Category A (EMI
WARRANTY	
Product Warranty Period (Worldwide)	2-year warranty, 3 year with registration. Note: <a <br="" class="insuranceLink">href="//www.tripplite.com/support/product-warranty-registration"&gt;Registration is required</a> for 3-year warranty.
Connected Equipment Insurance (U.S., Canada & Puerto Rico)	\$250,000 <a class="insuranceLink" href="//www.tripplite.com/support/insurance-policy">Ultimate Lifetime Insurance</a>

© 2020 Tripp Lite. All rights reserved. All product and company names are trademarks or registered trademarks of their respective holders. Use of them does not imply any affiliation with or endorsement by them. Tripp Lite has a policy of continuous improvement. Specifications are subject to change without notice. Tripp Lite uses primary and third-party agencies to test its products for compliance with standards. See a list of Tripp Lite's testing agencies: https://www.tripplite.com/products/product-certification-agencies